Automotive Electronics

Product Information CJ260

Monolithic B6 Bridge for Automotive Actuators





At a glance:

- ▶ Complete B6 bridge for automotive BLDC applications
- Integrated drivers
- ▶ High efficiency, low weight
- ▶ Peak power for high initial torque
- ▶ Powerful continuous drive
- ▶ Lowest electromagnetic emission
- ▶ Direct µC control
- ▶ Diagnosis and recovery functions
- Dual release concept for safety

Package

- ▶ PowerSSO-36
- Pitch 0.5mm
- ▶ Body 7.5 mm x 10.3 mm
- ▶ Power Pins ESD 4kV HBM w/o ext protection

Features


- Output stage with high side and low side drivers
- No charge pump and respective capacitor
- ▶ H-Bridge mode for DC motors
- ▶ Recovery strategies after incidents
- ▶ Slew rate control, four stages
- Output tri-state-mode in idle

Communication interface

- ▶ SPI
- Compatible with 3.3 and 5V logic μC
- ▶ Stands 18V over-voltage

Output stage protection against


- Uncontrolled activation of half-bridges
- Excessive / low supply voltage
- Over-current, especially in load dump
- ▶ Thermal damage
- ▶ Short and open load



Key Parameters

Parameter	Value
Power stage active at	4.5 V 28 V
Load dump pulse robustness	40 V
Inverse current robustness on V _s	5 A
Half bridge resistance at 3A, 150°C	max. 540 mΩ
Current limit setting, 3 ranges	5A 8.6 A
Continuous VS load current	3 A _{rms}
Digital supply voltage	4.5 V 5.25 V
Junction temperature	-40 °C 150 °C
Output switching frequency	max.20 kHz
Output rise/fall slew rate set at 3A	typ. 1.7 45 V/μs

Pins on PowerSSO36 package



Potential applications

- ▶ Throttle valve
- ▶ General Purpose Actuator
- ▶ Engine Compartment Actuator
- ▶ Electric Gearbox Oil Pump
- ▶ Accelerator Pedal Module
- Window Lifter Electronic Control Unit
- Sunroof Electronic Control Unit
- Windshield Electronic Control Unit
- Auxiliary Pump
- ▶ Pump Control Electronic
- ▶ Fuel Supply Module
- Electric fuel pump tank installation unit

All document:

Target values, subject to change without notice

Regional sales contacts

Europe/Japan bosch.semiconductors@de.bosch.com
USA/Canada bosch.semiconductors@us.bosch.com
China bosch.semiconductors@cn.bosch.com
Korea bosch.semiconductors@kr.bosch.com

www.bosch-semiconductors.com www.bosch-sensors.com

Robert Bosch GmbH

AE/MKC Postfach 13 42 72703 Reutlingen Germany

www.bosch.de

© Robert Bosch GmbH 07/2015. All rights reserved, also regarding any disposal, exploitation, reproduction, editing, distribution, as well as in the event of applications for industrial property rights. The information provided is for information purposes only and does not constitute a legal obligation or a warranty, express or implied, concerning quality, marketability or suitability for a specific purpose. The designs incorporated in vehicles and the performance of the designs may vary depending on the vehicle manufacturer's specifications and requirements for the product. We reserve the right to make product changes, adaptations and modifications without prior notice.